

# RISH MIT 30 Analog Digital Multimeter with Insulation Resistance Measurement

## Data Sheet

Analog Digital Multimeter  
with Insulation resistance



## Application :

**RISH MIT 30** is Analog Digital Multimeter with insulation resistance measurement , which measures VAC, VDC, VAC+DC, Frequency, mA DC, mA AC+DC, Resistance, continuity, Diode, Farad, AC current measurement with clip-on sensor and insulation resistance measurement.

## Product Features:

### Insulation resistance measurement up to 3GΩ.

Insulation resistance measurement up to 3GΩ with Test voltages selection: 50 V, 100V, 250V, 500V and 1000V.

### Route mean square value with distorted wave form.

Measuring principal employed permits the measurement of root mean square value (TRMS) OF AC quantities and mixed quantities (AC and DC) regardless of wave form.

### AC Current measurement with clip-on sensor

Current measurement up to 300A with clip-on sensor having ratio 1mv/10mA.

### Min/Max Function

By pressing min/max button instrument will start recording minimum and maximum readings.

### Temperature measurement

Temperatures from -200 to 800°C using pt100 and pt 1000 sensors.

### Auto Power Off

In order to save the power of the Batteries, the meter will automatically shut OFF if it detects no activity for 10 minutes.

### Continuity test

This permits testing for short circuit and open circuit. In addition to the display, a facility of sound signal is available.

### AUTO and MANUAL ranging modes.

In AUTO ranging mode the instrument automatically selects the range with best resolution depending on the applied input. In MANUAL ranging mode range is user selectable using **MAN** key.

### Indication of negative values on the analog scale.

When measuring DC quantities, also negative values are shown on the analog scale so that variations of the measured value can be observed at the Zero point.

### Protection from dust and water:

Instrument: Ip50 For terminals : IP20 as per IEC60529

### Applicable International Safety standards

1000 V CAT II/600V CAT III as per International Safety standard IEC 61010-1- 2001 and IEC 61557.

### Signaling in the case of a blown fuse.

The display shows "FUSE" in case of blown fuse.

### Automatic blocking socket(ABS)

The automatic terminal blocking system prevents incorrect connection of test lead and incorrect selection of measurement quantity, which provide safety to the user.

### Interface and software RISH com 100.

The multimeters are fitted with a serial RS-232 C interface via which the measured values can be transmitted to a PC. These values, electrically isolated, are transmitted to the attachable interface adaptor with infrared light through the case.

### Analog Scale

Analog scale that updates at the rate 20 times/sec to observe fluctuations in input.

### Continuous On Mode

In this mode, AUTO POWER OFF is disabled.

### DATA Hold Function

By pressing DATA HOLD button, reading on the display can be latched for Hands free operation.

### NULL ZERO Correction for Resistance

For Low ohm measurement, the lead resistance can be compensated by pressing the shift key (Yellow Key)

### NULL ZERO Correction for Capacitance

Null zero connection for capacitance. For nF range, stray capacitance can be compensated by shift key (Yellow Key)

### Diode Measurement


For testing diode and transistors, diode measurement function is available.

### Display with Backlit.

For clear visibility in dark conditions, RISH MIT 30 is featured with backlit.

## Specifications:

Measuring function	Measuring range	Resolution	Input impedance	Intrinsic error of digital display $\pm$ (...% of rdg + ...digit) at reference condition	Over load capacity <sup>1)</sup>	
					Over load value	Overload duration
V dc	30.00 mV	10 $\mu$ V	>10 G $\Omega$ // <40pF	0.5 + 3 <sup>2)</sup>	1000 V DC AC eff / rms Sine wave	Continuously
	300.0 mV	100 $\mu$ V	>10 G $\Omega$ // <40pF	0.5 + 3		
	3.000 V	1 mV	11 M $\Omega$ // <40pF	0.25 + 1		
	30.00 V	10 mV	10 M $\Omega$ // <40pF	0.25 + 1		
	300.0 V	100 mV	10 M $\Omega$ // <40pF	0.25 + 1		
V ~	1000 V	1 V	10 M $\Omega$ // <40pF	0.35 + 1		
	3.000 V	1 mV	11 M $\Omega$ // <40pF	1.0 + 3 (>10 Digits)		
	30.00 V	10 mV	10 M $\Omega$ // <40pF			
	300.0 V	100 mV	10 M $\Omega$ // <40pF			
1000 V	1V	10 M $\Omega$ // <40pF				
V AC+DC	3.000 V	1 mV	11 M $\Omega$ // <40pF	1.0 + 3 (>10 Digits)		
	30.00 V	10 mV	10 M $\Omega$ // <40pF			
	300.0 V	100 mV	10 M $\Omega$ // <40pF			
	1000 V	1V	10 M $\Omega$ // <40pF			
A AC with clamp 6)	30/300 A	10/100mA	–	0.5 +5	–	--
A DC	<b>Voltage Drop</b>				0.36 A	Continuously
	300.0 $\mu$ A	100 nA	15 mV	0.5+5 (>10 Digit)		
	3.000 mA	1 $\mu$ A	150 mV	0.5+2		
	30.00 mA	10 $\mu$ A	650 mV	0.5+5 (>10 Digit)		
AAC+DC	300.0 mA	100 $\mu$ A	1V	0.5+5	0.36 A	Continuously
	3.000 mA	1 $\mu$ A	150 mV	1.5+4 (>10 Digit)		
	300.0 mA	100 $\mu$ A	1 V	1.5+4 (>10 Digit)		
$\Omega$	<b>No load voltage</b>				1000 V DC AC eff / rms Sine wave	10 sec
	30.00 $\Omega$	10 m $\Omega$	Max. 3.2 V	0.5 + 3 <sup>2)</sup>		
	300.0 $\Omega$	100 m $\Omega$	Max. 3.2 V	0.5 + 3		
	3.000 K $\Omega$	1 $\Omega$	Max. 1.25 V	0.4 + 1		
	30.00 K $\Omega$	10 $\Omega$	Max. 1.25 V	0.4 + 1		
	300.0 K $\Omega$	100 $\Omega$	Max. 1.25 V	0.4 + 1		
	3.000 M $\Omega$	1 K $\Omega$	Max. 1.25 V	0.6 + 1		
$\rightarrow$	30.00 M $\Omega$	10 K $\Omega$	Max. 1.25 V	2.0 + 1		
$\rightarrow$	2.000 V	1 mV	Max. 3.2 V	0.25 + 1		

Measuring function	Measuring range	Resolution	Discharge resistance	U0 max.	Intrinsic error of digital display $\pm$ (...% of rdg + ...digit) at reference condition	Over load capacity <sup>1)</sup>	
						Over load value	Overload duration
Farad 	30.00 nF	10 pF	250 K $\Omega$	2.5 V	1.0 + 3 <sup>2)</sup>	1000 V DC AC eff / rms Sine	10 sec
	300.0 nF	100 pF	250 K $\Omega$	2.5 V	1.0 + 3		
	3.000 $\mu$ F	1 nF	25 K $\Omega$	2.5 V	1.0 + 3		
	30.00 $\mu$ F	10 nF	25 K $\Omega$	2.5 V	3.0 + 3		

Measuring function	Measuring range	Resolution	Discharge resistance	U0 max.	Intrinsic error of digital display $\pm$ (...% of rdg + ...digit) at reference condition	Over load capacity <sup>1)</sup>	
						Over load value	Overload duration
Hz			<b>f min V dc</b>	<b>f min V ~</b>	0.5 + 1 <sup>3)</sup>	$\leq$ 3 kHz 1000 v $\leq$ 30 kHz; 300 V $\leq$ 100 kHz 30 V	Continuously
	300.0 Hz	0.1 Hz	1 Hz	45 Hz			
	3.000 KHz	1 Hz	1 Hz	45 Hz			
	30.00 KHz	10 Hz	10 Hz	45 Hz			
%	2.0...98.0%	0.1 %	2 Hz	--	2 Hz... 1kHz $\pm$ 5 Digit <sup>4)</sup> 1 kHz ... 10 kHz; $\pm$ 5 Digit / kHz <sup>4)</sup>		
	$^{\circ}$ C	Pt 100	-200.0... +200.0 $^{\circ}$ C	0.1 $^{\circ}$ C	--	2 Kelvin + 5 Digit <sup>5)</sup>	1000 V DC AC eff / rms Sine
+200.0... +850.0 $^{\circ}$ C			0.1 $^{\circ}$ C	1.0 + 5 <sup>5)</sup>			
Pt 1000		-100.0... +200.0 $^{\circ}$ C	0.1 $^{\circ}$ C	--	2 Kelvin + 2 Digit <sup>5)</sup>		
		+200.0... +850.0 $^{\circ}$ C	0.1 $^{\circ}$ C		1.0 + 2 <sup>5)</sup>		

## Reference conditions for Accuracy:

Reference temperature	23°C ± 2K
Relative Humidity	45%...55% RH
Waveform of measured quantity	Sinusoidal
Input frequency	50 or 60 Hz ±2%
Battery Voltage	8 V ± 0.1 V

## Response time (After manual range selection):

Measured Quantity/ Measured Response time	Response Time		Transient response for step function of the measured quantity
	Of Analog indication	Of digital indication	
VDC, VAC, AAC+DC, AAC	0.7 s	1.5 s	From 0 to 80 % of upper range limit.
30Ω...3 MΩ	1.5 s	2 s	
30 MΩ	4 s	5 s	From ∞ to 50 % of upper range limit.
	0.7s	1.5s	
nF, μF, °C,		Max. 1... 3 s	
300 Hz, 3KHz		Max 2 s	From 0 to 80 % of upper range limit.
30 KHz, 300 KHz		Max 0.7 s	
% (1 Hz)		Max 9 s	
% (≥10 Hz)		Max 2.5 s	

## Environmental

Operating temperature	-20 to +50°C
Storage temperature	-25 to +70°C
Relative humidity	<75% non condensing.
Terminal Protection	IP20 for terminals
Altitude	Up to 2000 m

## Battery

Battery Voltage	6 x 1.5 V Cells
Battery type	Alkaline manganese Dioxide cell as per IEC LR 03 , ANSI 24A (Size AAA)
Battery Life	Minimum 600 hours on Vdc, Adc ,240 hours on Vac, Aac, For MΩISO @1000 V, 800 Measurements possible with nominal current MΩISO @500,250V, 100V, 50 V, 2400 Measurements possible with nominal current.

## Interface

Type	RS232C, serial, as per DIN 19241.
Data transmission	Optically with infrared light through the case.
Baud rate	8192 bits/s.

## Influence Quantities and Variations:

Influence Quantity	Measuring Range	Resolution	Intrinsic error of digital display ± (...% of rdg + ...digit) at reference condition
V1MΩ <sup>7)</sup>	0...1000 V AC+DC	1V	1+10 D
MΩIT@1000V 8)	0...1000 V AC+DC	1V	1+10 D
MΩIT Un=50 V	0.100...1.600 MΩ	1KΩ	--
	01.40...16.00 MΩ	10 KΩ	5 + 15 D
MΩIT Un=100 V	014.0...155.0 MΩ	100 KΩ	--
	0.100...3.100 MΩ	1KΩ	--
	02.80...31.00 MΩ	10 KΩ	5 + 15 D
MΩIT Un=250 V	028.0...310.0 MΩ	100 KΩ	--
	0.100...0.800 MΩ	1KΩ	--
	00.70...08.00 MΩ	10 KΩ	3 + 10 D
	007.0...080.0 MΩ	100 KΩ	--
MΩIT Un=500 V	0070...0775 MΩ	1MΩ	--
	0.100...1.600 MΩ	1KΩ	--
	01.40...16.00 MΩ	10 KΩ	3 + 10 D
	014.0...160.0 MΩ	100 KΩ	--
MΩIT Un=1000 V	0140...1600 MΩ	1MΩ	--
	0.100...3.100 MΩ	1KΩ	--
	02.80...31.00 MΩ	10 KΩ	3 + 10 D
	028.0...310.0 MΩ	100 KΩ	--
	0280...3100 MΩ	1MΩ	--

- 1) At 0° .... + 40 °C
- 2) With zero adjustment, without zero adjustment + 50 digits
- 3) Range
  - 3 V ac/dc: Ue = 1.5 V eff/rms ... 100 V eff/rms
  - 30 V ac/dc: Ue = 15 V eff/rms ... 300 V eff/rms
  - 300 V ac/dc: Ue = 150 V eff/rms ... 1000 V eff/rms
- 4) On the range 3 V dc, square – wave signal positive on one side 5 ... 15 V,  
f = const., not 163.84 Hz or integral multiple.
- 5) Without sensor.
- 6) Measurement with clip-on current sensor with ratio 1mv/10mA.
- 7) Discharge the DUT through 1MΩ resistance, before insulation resistance measurement. LCD displays value of voltage present on DUT.
- 8) In this switch position live circuit detection (V AD+DC) is done before insulation measurement. If voltage present is greater than 50V (AC+DC), insulation resistance measurement function is disabled and LCD displays value of voltage present on DUT.

Influence Quantity	Range of Influence	Measured Quantity / measuring Range	Variation <sup>1)</sup> ± (...% of rdg. + ....digits)
Temperature	0 °C +21 °C and +25 °C...+40°C MΩIT 0.25 + 2	30/300 mV dc	1.0 + 3
		3...300 V dc	0.15 + 1
		1000 V dc	0.2 + 1
		V ~	0.4 + 1
		300µA ... 300mA DC	0.5+1
		A AC+DC	0.75+3
		30 Ω 2)	0.15 + 2
			300 Ω 0.25 + 2
		3 KΩ – 3 MΩ	0.15 + 1
		30 MΩ	1.0 + 1
		30 nF <sup>2)</sup> – 3 µF	0.5 + 2
		30 µF	2.0 + 2
		Hz	0.5 + 1
		%	± 5 digits
Frequency of the measured quantity	15 Hz...< 30 Hz	3...1000 V ~	1.0 + 3
	30 Hz...< 45 Hz		0.5 + 3
	> 65 Hz... 400 Hz		2.0 + 3
	>400 Hz...1 KHz		3.0 + 3
	20Hz ...< 45 Hz		3.0 + 7
	>66 Hz... 1 kHz		2.0 + 3
Wave form of the measured quantity <sup>3)</sup>	Crest factor CF	V ~ 4), A~ 4)	± 1 % of rdg
			± 3 % of rdg
Battery Voltage	⎓ <sup>5)</sup> ...< 7.9 V > 8.1 V ...10.0 V	V DC	2 Digit
		V~, ADC	4 Digit
		A AC+DC	6 Digit
		30Ω / 300 Ω/°C	4 Digit
		3 kΩ – 30MΩ, MΩIT	3 Digit
		nF, µF,	1 Digit
		Hz	1 Digit
%	1 Digit		
Relative humidity	75%	V~,V DC A AC+DC,A DC	3 Days
	3 Days	Ω	1 x intrinsic error
	Meter off	Hz °C	
DATA	-	%	± 1 digits
MIN/MAX	-	V ac/dc , A ac/dc, clamp	± 2 digits

- 1) With temperature: Error data apply per 10 K change in temperature.  
With frequency: Error data apply to a display from 300 digits onwards.
- 2) With zero adjustment.
- 3) With unknown waveform (crest factor CF > 2), measure with manual range selection
- 4) With the exception of sinusoidal waveform.
- 5) After the “⎓” symbol is displayed.

Influence Quantity	Range of Influence	measuring Range	Attenuation
Common Mode interference voltage	Noise quantity max. 1000 V	V dc 3V~ , 30V~ 300 V~	> 120 dB > 70 dB
		1000 V~	> 60 dB
Normal Mode Interference Voltage	Noise quantity max. 1000 V ~ Value of the measuring range at a time Max. 1000V~ ,50Hz, 60Hz sinusoidal	V dc	50dB
	Noise quantity max. 1000 V-	V~	>110dB

### Applicable Standards:

For Use as a Insulation Measuring Instrument.

IEC 61557: Devices for testing, measuring and monitoring protective safety measures in system with voltages of up to 1000 V A.C. and 1500 V D.C.

IEC 61557- 1: For general requirements

IEC 61557- 2: For Insulation resistance measuring instruments

IEC 61326: Class B

IEC 61000-4-2 8 KV atmosphere discharge, 4 KV contact discharge

IEC 61000-4-3 : 3 V/m

EMC

Immunity

### Safety

IP for water & dust

Pollution degree:

Installation category:

High Voltage Test

IEC 61010-1-2001

IEC60529

2

III

3.5 kV (IEC 61010-1-2001)



Measure



Control



Record



Analyze



Optimize

## RISHABH INSTRUMENTS LIMITED

Domestic (India): +91 253 2202099 | marketing@rishabh.co.in

International: +91 253 2202004/06/08/99 | global@rishabh.co.in

www.rishabh.co.in